

Diesel Generating Set

BF142-60

MODEL	BF142-60
Standby Power (60Hz)	114KW / 142KVA
Prime Power (60Hz)	104KW / 130KVA

Standard Features

General Features:	
Engine (BaiFa CA6DF2-18D)	
Radiator 40 ^o C max, fans are driven by belt, with safety	
guard	
12V charge alternator	
Alternator: single bearing alternator IP23, insulation	
class H/H	
Absorber	
Dry type air filter, fuel filter, oil filter	
Main line circuit breaker	
Standard control panel	
12V batteries, rack and cable	
Ripple flex exhaust pipe, exhaust siphon, flange, muffler	
User manual	

Generator Ratings

Voltage	HZ	Phase	P.F (COS¢)	Standby Amps	Standby Ratings (KW/KVA)	Prime Ratings (KW/KVA)
230/132	60	3	0.8	356	114/142	104/130

Prime Power (PRP): Prime power is available for an unlimited number of annual hours in variable load application, in accordance with GB/T2820-97 (eqv ISO8528); A 10% overload capability is available for a period of 1 hour within a 12-hour period of operation.

Standby Power Rating (ESP): The standby power rating is applicable for supplying emergency power for the duration of a utility power interruption. No overload, utility parallel or negotiated outage operation capability is available at this rating.

Sales Promises

Baifa Power provides a full line of brand new and high quality products. Each and every unit is strictly factory tested.

Warranty is according to our standard conditions: a, 15 months, counted on the day BAIFA sold to the first buyer; b, One year after installation; c, 1000 running hours (accumulated); subject to the earlier one.

Service and parts are available from Baifa Power or distributors in your location.



Diesel Generating Set

BF142-60

Manufacturer / Model:	BaiFa CA6DF2-18D, 4-cycle		
Air Intake System:	Turbocharged		
Fuel System:	Direct injection		
Cylinder Arrangement:	6 in line		
Displacement:	7.13L		
Bore and Stroke:	110×125 (mm)		
Compression Ratio:	17		
Rated RPM:	1800rpm		
Max. Standby Power at Rated RPM:	145KW/197.3HP		
Governor Type:	Electronic		
Exhaust System			
Exhaust Gas Flow:	25m ³ /min		
Exhaust Temperature:	470°C		
Max Back Pressure::	6.7kpa		
Air Intake Syste	em		
Burning Capacity:	9m ³ /min		
Max intake restriction:	6.3kpa		
Fuel System			
100%(Prime Power) Load:	202g/kWh		
75%(Prime Power) Load:			
50%(Prime Power) Load:			
100%(Prime Power) Load:	29.4L/h		
Oil System			
Total Oil Capacity:	23L		
Oil Consumption:	0.06L/h		
1			

Cooling System	
Max Water Temperature:	97 ±2 ℃

ALTERNATOR SPECIFICATION



GENERAL DATA

Compliance with GB755, BS5000, VDE0530, NEMAMG1-22, IED34-1, CSA22.2 and AS1359 standards.

Alternator Data				
Number of Phase:	3			
Connecting Type:	3Phase and 4Wires, "Y" type connecting			
Number of Bearing:	1			
Power Factor:	0.8			
Protection Grade:	IP23			
Altitude:	≤1000m			
Exciter Type:	Brushless, self-exciting			
Insulation Class, Temperature Rise:	H/H			
Telephone Influence Factor (TIF):	<50			
THF:	<2%			
Voltage Regulation, Steady State:	<u>≤</u> ±1%			
Alternator Capacity:	150KVA			
Alternator Efficiencies:	91.6%			

GENERATING SET DATA

Voltage Regulation:	≥±5%
Voltage Regulation, Stead State:	<u>≤</u> ±1%
Sudden Voltage Warp (100% Sudden Reduce):	≤+25%
Sudden Voltage Warp (Sudden Increase):	≤-20%
Voltage Stable Time (100% Sudden Reduce):	≤6S
Voltage Stable Time (Sudden Increase)	≤6S
Frequency Regulation, Stead State:	≤5%
Frequency Waving:	≤1.5%
Sudden Frequency Warp (100% Sudden Reduce):	≤+12%
Sudden Frequency Warp (Sudden Increase):	≤-10%
Frequency Recovery Time (100% Sudden Reduce):	≤5S
Frequency Recovery Time (Sudden Increase):	≤5S



- Saifa Standard Auto Control System
- \diamond Base Fuel Tank
- \diamond Starting

batteries(Maintenance-Free & Watering-Free) with connective wires

Options

- ♦ Daily Fuel Tank
- ♦ Battery Charger
- \diamond Engine Heater
- \diamond Alternator Heater
- \diamond Water Separator

Dimension & Weight

- Permanent Magnet
 Generator(PMG)
- ♦ Rainproof Type
- \diamond Soundproof Type
- \diamond Trailer Type

♦ MCCB

 \diamond Oil Drain Valve

until muffler)

♦ Exhaust System(including


 \diamond Paralleling System

- One set of fuel filter / oil filter / belt
- \diamond Documents

- ♦ Remote Control Panel
- \diamond Automatic Transfer Switch
- \diamond Switch box
- \diamond Spare Parts

Open Type with Base Fuel Tank

Overall Size: 2310×940×1600 (mm) Weight: 1600 kg



Soundproof Type

 $Overall \ Size: 2810 \times \!\! 1140 \times \!\! 1830 \pmod{mm}$

Weight: 2200kg

Trailer Type

Overall Size:3390×1720×2470 (mm) Weight: 2860kg





Auto Module Control Panel

Baifa Standard Control Panel uses micro processing technique integrating digital, intelligent and network techniques which can carry out functions including auto start/stop, data measure, alarming. The controller uses LCD display, optional Chinese and English display interface with operation easy and reliable. It can be widely used in all types of generator automatic control system for compact structure, advanced circuits, simple connections and high reliability



Auto Module Control Panel is the configuration for nobody on duty controlling generators. This kind of panel adopts auto module control system, with large LCD display to show the menu.

Features: MRS10-can receive remote output signal from ATS and realize auto start and stop of generators.

MRS16-can realize all functions of MRS10, add RS232 interface which can communicate with PC to realize remote operation.

AMF25-Auto Mains Failure controller, can realize all functions of MRS16, furthermore can detect ATS and control directly.